

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

S4-01P6203

Semiconductor configuration comprising a highly doped channel
conduction region and method for producing a semiconductor
5 configuration

The invention relates to a semiconductor configuration for
controlling a current, the semiconductor configuration
comprising at least a first semiconductor region of a first
10 conductivity type (n or p), a current path running at least
partially within the first semiconductor region, and a channel
region, which is part of the first semiconductor region, which
has a basic doping and within which the current can be
influenced by means of at least one depletion zone. Such a
15 semiconductor configuration is disclosed in US 6,034,385, for
example. Moreover, the invention relates to a method for
producing a semiconductor configuration.

In order to supply an electrical load with a rated electric
20 current, the load is usually connected to an electrical supply
network via a switching device. During the switch-on operation
and also in the case of a short circuit, an overcurrent occurs
which lies significantly above the rated current. In order to
protect the electrical load, the switching device connected
25 between the load and the electrical network must be able to

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

limit and also switch off said overcurrent. Furthermore, in converter technology, for example, there are applications in which the load, in the case of a voltage present in the reverse direction, is also intended to be reliably isolated
5 from the supply network. Current-limiting switches in the form of a semiconductor configuration are known for the functions described.

Thus, US 6,034,385 and also WO 00/16403 A1 describe a
10 semiconductor configuration, in which a current flow between a first and a second electrode is controlled. In particular the current can be switched on and off or be limited to a maximum value. The active part of the semiconductor configuration comprises a first semiconductor region of a predetermined
15 conductivity type, in particular the n conductivity type. The conductivity type is determined by the type of charge carriers with which the semiconductor region is doped. For current control, at least one lateral channel region is provided within the first semiconductor region. In this case, lateral
20 or else horizontal is understood to mean a direction parallel to a main surface of the first semiconductor region. By contrast, vertical denotes a direction running perpendicularly to the main surface. The lateral channel region is bounded in the vertical direction by at least one p-n junction, in
25 particular by the depletion zone (zone with depletion of

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

charge carriers and hence high electrical resistance; space charge zone) of said p-n junction. The vertical extent of said depletion zone can be set inter alia by a control voltage. The p-n junction is formed between the first semiconductor region and a buried p-conducting island region. The buried island region undertakes the shielding of the first electrode with respect to the high electric field in the reverse direction or in the switched-off state. In specific embodiments, the channel region can also be bounded by a further depletion zone in the vertical direction. Said further depletion zone is brought about for example by a further p-n junction between a second p-conducting semiconductor region and the first n-conducting semiconductor region. The second p-conducting semiconductor region can also be connected to a control voltage by means of a control electrode. The channel region that is crucial for the current control is arranged within an epitaxial layer. Fluctuations in thickness and dopant concentration may occur during the production of said epitaxial layer. This directly affects the current-controlling properties of the channel region. It is possible, therefore, for the semiconductor configuration not to have the required current control behavior, for example a specific pinch-off voltage, at the end of the production process on account of the tolerances of the epitaxial layer. The achievable yield thus decreases.

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

A similar semiconductor configuration is described in DE 196 29 088 A1. Consequently, a similarly low technology-dictated yield may occur during production in the case of this semiconductor configuration as well.

5

US 6,232,625 discloses a passive embodiment of the above-described semiconductor configuration according to US 6,034,385. The second p-conducting semiconductor region is also connected to the first electrode. A construction without active current control then results, that is to say that the current flow through the semiconductor configuration cannot be influenced by an external control voltage. Rather, the semiconductor configuration disclosed is a passive current limiter.

15

Furthermore, US 5,543,637 discloses a semiconductor configuration which comprises a first semiconductor region of a first conductivity type with a buried island region of a conductivity type opposite to the first, and also two electrodes and a control electrode. The respective depletion zones brought about by the control electrode and the buried island region again form a channel region in which a current flowing between the two electrodes is controlled. The control electrode is embodied either as a Schottky contact or as a MOS contact. 3C, 6H or 4H silicon carbide (SiC) is used as

25

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

semiconductor material. In this case, too, the channel region is arranged in an epitaxial layer whose thickness and dopant concentration are subjected to fluctuations.

5 Furthermore, DE 198 33 214 C1 discloses a semiconductor configuration which is realized using SiC, in particular, and in which an n-conducting lateral channel region bounded by two p-conducting semiconductor regions is provided for current control. The channel region is once again situated in an
10 epitaxial layer, so that in this case, too, a reduced yield is possible during production for the reasons mentioned above.

US 6,150,671 and US 5,923,051 describe semiconductor configurations each in the form of an SiC-MOSFET. In this
15 case, channel regions are again situated in a p-conducting and respectively in an n-conducting layer grown epitaxially.

The invention is based on the object of specifying a semiconductor configuration of the type referred to in the
20 introduction, which, during production, is insensitive to technology-dictated fluctuations and enables a high yield. Moreover, the intention is to specify a method for producing such a semiconductor configuration.

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

A semiconductor configuration in accordance with the features of the independent patent claim 1 is specified in order to achieve the object relating to the semiconductor configuration.

5

The semiconductor configuration according to the invention for controlling a current is a semiconductor configuration of the type referred to in the introduction in which the channel region advantageously comprises a channel conduction region intended for carrying current and having the first conductivity type and a higher doping compared with the basic doping.

The invention is based on the insight that a zone that is additionally provided in the channel region and has a higher dopant concentration compared with the rest of the channel region can considerably reduce, if not even completely eliminate, the sensitivity of the semiconductor configuration toward technology-dictated fluctuations during production. The additionally provided zone, which is referred to here as channel conduction region, is doped with dopants of the same charge carrier type (n or p) as the channel region. It essentially determines the electrical properties of the channel region. The current is thus preferably carried in the channel conduction region in on-state operation on account of

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

the higher doping and the higher conductivity accompanying this. By contrast, the rest of the channel region remains largely free of current, so that fluctuations in the basic doping or thickness that are present here, for instance, are then unimportant or only of secondary importance. The channel conduction region may be produced for example by means of ion implantation with very high accuracy and small fluctuations in dopant concentration and thickness. This new independence thus afforded with respect to the technology-dictated fluctuations results in an increased yield in the process for producing the semiconductor configuration.

Advantageous refinements of the semiconductor configuration according to the invention emerge from the claims dependent on claim 1.

In one favorable embodiment, the channel conduction region contains at least 80% of the total charge of the first conductivity type that is present overall in the channel region. Thus, at most only the remaining 20% of the total charge, situated outside the channel conduction region in the channel region, is subjected to the technology-dictated fluctuations. This positive effect can be increased further in that even at least 90% of the total charge of the first

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

conductivity type present within the channel region is
provided in the channel conduction region.

A so-called vertical semiconductor configuration is favorable,
5 in the case of which the current is guided essentially in the
vertical direction through the semiconductor configuration.
This embodiment is capable of carrying a particularly high
reverse voltage in the off-state situation. However, a lateral
semiconductor configuration with a current flow that
10 essentially runs in the lateral direction through the
semiconductor configuration is also possible, in principle.

The current control is effected by means of a preferably
lateral channel region. In this embodiment, it is possible
15 both for the current that is to be carried to be reliably
switched on and off and for a high reverse voltage to be taken
up by the semiconductor configuration.

In a further preferred variant, the semiconductor
20 configuration is present in the form of a field effect
transistor, in particular in the form of a junction field
effect transistor (JFET). This type of transistor is
particularly well suited to the current control desired in
connection with the present invention.

25

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

In one advantageous refinement, the semiconductor configuration is composed partially or else completely of a semiconductor material having a band gap of at least 2 eV. Examples of suitable semiconductor materials are diamond, gallium nitride (GaN), indium phosphite (InP) or preferably silicon carbide (SiC). The abovementioned semiconductor materials, in particular SiC, are very advantageous on account of the extremely low intrinsic charge carrier concentration (= charge carrier concentration without doping) and the very low on-state loss. Moreover, the abovementioned semiconductor materials have a significantly higher breakdown strength compared with the "universal semiconductor" silicon, so that the semiconductor configuration can be used at a higher voltage. The preferred semiconductor material is silicon carbide, in particular monocrystalline silicon carbide of the 3C or 4H or 6H or 15R polytype.

Furthermore, a variant is possible in which the semiconductor configuration comprises an island region that is at least partially buried within the first semiconductor region. Said island region has a second conductivity type (p or n) opposite to the first conductivity type (n or p). The island region forms a p-n junction with the first semiconductor region, the depletion zone of which p-n junction can be used for

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

controlling the channel region and hence also the current
flow.

In another advantageous embodiment, at least one channel
5 compensation region is arranged within the channel conduction
region. The channel conduction region preferably contains a
plurality of said channel compensation regions. The channel
compensation region has, in particular, a doping with a second
conductivity type (p or n) opposite to the first conductivity
10 type (n or p). When reverse control voltage is present, the
charge present in the channel compensation regions compensates
for the charge present in the channel conduction region, so
that it is possible to further increase the dopant
concentration of the first charge carrier type in the channel
15 conduction region. By virtue of the compensation, this does
not lead to an impairment of the electrical behavior of the
semiconductor configuration; in particular, this does not lead
to an undesirable increase in the control voltage (= pinch-off
voltage) required for the complete pinch-off of the channel
20 region. This affords advantages particularly when a small
pinch-off voltage of less than 15V, for example, is required.
Starting from an increase in the dopant concentration of the
first conductivity type in the channel conduction region by at
least the factor 2 compared with the embodiment without
25 channel compensation regions, the loss of area due to the

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

compensation regions is at least made up for, if not even over
compensated, on account of the then considerably increased
conductivity in the channel conduction region.

5 It is advantageous if the at least one channel compensation
region or, in the case of a plurality of channel compensation
regions, the individual channel compensation region in each
case has or have a higher dopant concentration than the
channel conduction region. The area proportion of the channel
10 conduction region is then greater than that of all the channel
compensation regions. This is favorable since the current is
intended to be carried within the channel conduction region
and, therefore, a maximum proportion of the channel conduction
region should also be available for this. At the same time,
15 the advantageous compensating effect described is preserved in
the off-state situation.

Preference is given to a refinement in which the total charge
of the first conductivity type that is present overall in the
20 channel conduction region is approximately equal in magnitude
to the total charge of the second conductivity type present in
all the channel compensation regions. A very good compensation
effect is then achieved.

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

In another advantageous variant, the channel region is arranged within an epitaxial layer. The technology-dictated fluctuations in the dopant concentration and thickness within the epitaxial layer are unimportant on account of the additionally present channel conduction region for the reasons mentioned above. Furthermore, it is possible for the first semiconductor region to have a second epitaxial layer, which is formed in particular as a drift zone which, in the off-state situation, takes up a substantial part of the reverse voltage present. The two epitaxial layers fulfill different tasks in each case. One serves for current control, and the other for taking up reverse voltage. In an expedient manner, it is nevertheless possible, in a further variant, for both epitaxial layers to have an essentially identical basic doping. By virtue of the channel conduction region that critically determines the current control behavior, the basic doping of the epitaxial layer in which the channel region is arranged may be designed according to other standpoints. This is because it is favorable for no jump in doping to occur at the interface between the two epitaxial layers. The semiconductor configuration can then carry a higher reverse voltage.

Furthermore, there is a variant in which the first semiconductor region is arranged on a substrate having the

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

opposite conductivity type to the first conductivity type.

Both charge carrier types - electrons and holes - are then

involved in carrying the current. A very favorable current

conduction behavior is established on account of the bipolar

5 modulation. Moreover, the additional p-n junction between the first semiconductor region and the substrate gives rise to suitability for a high reverse voltage.

In principle, the channel conduction region can advantageously

10 be used both in the case of a normally-on semiconductor configuration and in the case of a normally-off semiconductor configuration.

A method in accordance with the features of claim 17 is

15 specified in order to achieve the object relating to the method. The method according to the invention for producing a semiconductor configuration for controlling a current is a method in which at least a semiconductor substrate is provided, an epitaxial layer with a basic doping is applied to
20 the semiconductor substrate, the epitaxial layer comprising a channel region, within which the current can be influenced, and a channel conduction region intended for carrying current and having a higher doping compared with the basic doping is implanted into the epitaxial layer at least in the region of
25 the channel region.

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

This method is advantageous in particular because usually only a basic doping with a relatively high fluctuation range of approximately $\pm 15\%$, for example, can be produced by means of an epitaxy method. By means of an ion implantation used for producing the channel conduction region, by contrast, the doping can be set significantly more precisely. The channel conduction region which is critical for the current control, then has only very little fluctuation in its dopant concentration.

10

Refinements of the method in accordance with the claims dependent on claim 17 are advantageous.

What is particularly advantageous is a method variant in which a further epitaxial layer is applied to the semiconductor substrate. The two epitaxial layers are preferably applied to the semiconductor substrate progressively and one above the other. It is favorable, moreover, for the two epitaxial layers to have essentially the same basic doping. The ion implantation of the channel conduction region takes place after the conclusion of the epitaxial method steps for the application of the two epitaxial layers. This method makes it possible, with a high yield, to produce a semiconductor configuration which is intended for current control and has, in particular, the advantages mentioned above.

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

Preferred, but in no way restrictive, exemplary embodiments of the invention will now be explained in more detail with reference to the drawing. For illustration purposes, the drawing is not to scale, and certain features are represented diagrammatically. In detail:

Fig. 1 and Fig. 2 show a semiconductor configuration with a highly doped channel conduction region arranged within a channel region, and

10

Fig. 3 shows the doping profile of the channel conduction region provided in the semiconductor configuration of Fig. 1 and 2,

15 Fig. 4 shows a further semiconductor configuration with a channel conduction region and channel compensation regions,

Fig. 5 shows a cross section through the channel conduction region and the channel compensation regions of the semiconductor configuration of Fig. 4, and Fig. 6 to Fig. 8 show a further semiconductor configuration with a channel conduction region.

Mutually corresponding parts are provided with the same reference symbols in figures 1 to 8.

25

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

Fig. 1 illustrates a semiconductor configuration 100 for controlling a current I in the form of a vertical junction field effect transistor (JFET). The semiconductor configuration shown in figure 1 is merely a half-cell.

5 Mirroring at the right-hand edge of the half-cell yields a complete cell. A multicell structure is accordingly produced by multiple mirroring.

The active part, in which the current control essentially takes place, is contained in an n-conducting (electron conduction) first semiconductor region 2. Arranged within the first semiconductor region 2 is a p-conducting (hole conduction) buried island region 3. The first semiconductor region 2 has a first surface 20 and the buried island region 3 has a second surface 80. The two surfaces 20 and 80 essentially run parallel to one another. In the exemplary embodiment of figure 1, the first semiconductor region 2 is composed of a semiconductor substrate 27 and two epitaxially grown semiconductor layers 261 and 262 arranged thereon. The first surface 20 is associated with the second epitaxial layer 262 and the second surface 80 is associated with the first epitaxial layer 261. The two epitaxial layers 261 and 262 essentially have an identical basic doping. They are more lightly doped (n^-) than the semiconductor substrate 27 (n^+).

25

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

An n-conducting contact region 5 embedded within the island region 3 is provided at the second surface 80. It is highly doped (n^+). The island region 3 extends further than the contact region 5 in all directions parallel to the first surface 20.

Silicon carbide (SiC) is used as semiconductor material in the semiconductor configuration 100. It is particularly well suited, in particular at high voltages, on account of its specific material properties. Preferred dopants are boron and aluminum for a p-type doping and nitrogen and phosphorus for an n-type doping. The dopant concentration of the contact region 5 typically lies between $1 \times 10^{19} \text{ cm}^{-3}$ and $1 \times 10^{20} \text{ cm}^{-3}$ and that of the two epitaxial layers 261 and 262 is typically a maximum of $5 \times 10^{16} \text{ cm}^{-3}$. In this case, the symbol "x" is used as a multiplication symbol. The doping of the first epitaxial layer 261 depends, in particular, on the reverse voltage that is to be taken up by the semiconductor configuration 100 in the off-state situation. The higher the reverse voltage, the lower said doping. The epitaxial layer 261 essentially has to carry the electric field to be blocked. In the example shown, both epitaxial layers 261 and 262 have a basic doping of approximately between $5 \times 10^{15} \text{ cm}^{-3}$ and $7 \times 10^{15} \text{ cm}^{-3}$. The reverse voltage is then at least 1200 V.

25

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

The buried island region 3 and the contact region 5 embedded therein are preferably produced after the application of the first epitaxial layer 261. In this case, it is possible to employ in particular the self-aligning masking technique described in US 6,204,135 B1. The island region 3 and the contact region 5 are accordingly produced by means of two masking steps and ion implantation of p-type and n-type dopant particles into the second surface 80. Afterward, the second epitaxial layer 262 is applied in a second epitaxial growth step.

A contact hole 70 is provided within the second epitaxial layer 262, which contact hole extends in the vertical direction as far as the second surface 80. The contact hole 70 uncovers both a part of the buried island region 3 and a part of the contact region 5, so that the two regions 3 and 5 can be subjected to ohmic contact-connection by means of a first electrode 50 made of an electrically conductive material. The contact region 5 and the island region 3 are short-circuited by the first electrode 50. Polysilicon or a metal, preferably nickel, aluminum, tantalum, titanium or tungsten, is appropriate as material for the first electrode 50. The contact hole 70 is produced by means of a dry etching process, for example. In order to compensate for fluctuations in the etching depth, in accordance with an embodiment that is not

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

illustrated, it is also possible to provide a plurality of
_____ contact holes 70, which then each have a smaller diameter.

A second electrode 60 is provided on a side of the first
5 semiconductor region 2, which is remote from the first surface
20. The current I flowing through the semiconductor
configuration 100 is conducted in and away by means of the two
electrodes 50 and 60. On account of the essentially vertical
current path, that is to say current path running
10 perpendicular to the first surface 20, the semiconductor
configuration 100 is also referred to as vertical.

Arranged laterally beside the contact hole 70 is a first
depletion zone 24, which adjoins the first surface 20 and is
15 situated within the first semiconductor region 2. Furthermore,
there is a p-n junction present between the first
semiconductor region 2 and the buried island region 3, the
depletion zone of which p-n junction is designated here as
second depletion zone 23. The second depletion zone 23
20 surrounds the entire buried island region 3. In so far as the
two depletion zones 23 and 24 extend within the first
semiconductor region 2, they are depicted by dashed lines in
figure 1. The first and second depletion zones 24 and 23,
respectively, bound a lateral channel region 22 in the
25 vertical direction, which channel region lies within the first

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

semiconductor region 2 and is part of the current path between the first and second electrodes 50 and 60, respectively. The first depletion zone 24 and the buried island region 3 are arranged in such a way that the two depletion zones 23 and 24 overlap at their lateral edges in a projection onto the first surface 20. The lateral channel region 22 is situated precisely within this overlap region.

In the lateral direction, the lateral channel region 22 is bounded by an edge 221 on the side facing the contact hole 70. Said edge 221 is formed by a projection of the contact region 5 into the first semiconductor region 2, which projection is performed perpendicularly to the first or second surface 20 or 80, respectively. Specifically, the second depletion zone 23 serving as lower vertical boundary no longer extends into the first semiconductor region 2 starting from the location at which the heavily n-doped contact region 5 is arranged within the island region 3. The p-n junction, which is critical for such a depletion zone, runs starting from this location between the n-conducting contact region 5 and the p-conducting island region 3. The lateral edge 221 is thus determined by the position of the contact region 5 within the island region 3. By contrast, the second lateral edge (not specifically designated in figure 1) of the lateral channel region 22 is determined by the lateral dimensioning of the island region 3.

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

These geometric parameters can be established very accurately
by the structuring method described in US 6,204,135 B1.

The first depletion zone 24 and the contact region 5 are
5 arranged in such a way in relation to one another that they
overlap by 1 to 2 μm at their lateral edges in a projection
into a common plane which is performed perpendicularly to the
first or second surface 20 or 80, respectively. This
last-mentioned overlap ensures that the lateral edge 221
10 actually reaches directly as far as the contact region 5.

The length (= lateral extent) of the lateral channel region 22
is typically between 1 μm and 5 μm in the case of a
semiconductor configuration 100 produced from silicon carbide.
15 The lateral channel region 22 is preferably made as short as
possible. This results in a highly compact overall
construction with a small space requirement. The vertical
extent typically lies between 0.5 μm and 2 μm in the voltage-
and current-free state. The depletion zones 23 and 24 are
20 characterized by a high degree of depletion of charge carriers
and thus have a significantly higher electrical resistance
than the lateral channel region 22 bounded by them in the
vertical direction. The spatial extent of the two depletion
zones 23 and 24, in particular that in the vertical direction,

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

varies in a manner dependent on the prevailing current and
voltage conditions.

The lateral channel region 22 thus critically determines the
5 (control) behavior of the entire semiconductor configuration
100. When designed as a current limiter, the behavior in the
presence of an operating voltage in the forward direction
depends on the electric current I flowing through the
semiconductor configuration 100 between the two electrodes 50
10 and 60. As the current intensity rises, the forward voltage
drop increases between the electrodes 50 and 60 on account of
the bulk resistance. This leads to an enlargement of the
depletion zones 23 and 24 and, consequently, to a reduction of
the current-carrying cross-sectional area in the lateral
15 channel region 22, which reduction is associated with a
corresponding increase in resistance. Upon reaching a specific
critical current value (= saturation current), the two
depletion zones 23 and 24 touch and completely pinch off the
lateral channel region 22.

20

Such a channel pinch-off can also be achieved by applying a
control voltage to the semiconductor configuration 100 in
particular such that the first depletion zone 24 is enlarged
in the vertical direction. The control voltage that has to be
25 applied given a vanishing voltage between the first and second

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

electrodes 50 and 60, respectively, in order to achieve a
channel pinch-off is also called pinch-off voltage.

The current path between the first and second electrodes 50
and 60, respectively, comprises, in the forward direction, the
contact region 5, the lateral channel region 22, a vertical
channel region 21 arranged in the first semiconductor region
2, and a subsequent drift zone composed of the remaining part
of the first epitaxial layer 261 and the substrate 27.

By contrast, upon application of an operating voltage in the
reverse direction, the current flow takes place essentially
via a backward diode 90 formed by the buried island region 3
and the underlying part of the first semiconductor region 2.

The behavior of the lateral channel region 22, which is
critical for the current control, is determined in particular
by the second epitaxial layer 262. The properties of the
second epitaxial layer 262 influence in particular the
pinch-off voltage, a voltage which is applied for controlling
the first depletion zone 24 and starting from which a current
flow occurs between the depletion zone 24 and the buried
island region 3 (= punch-through voltage), the maximum current
I flowing between the two electrodes 50 and 60 (= saturation
current), the electrical resistance in the channel region 22

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

and also to a certain extent the maximum permissible reverse voltage. The properties of the second epitaxial layer 262 may then have technology-dictated fluctuations, however. Thus, the dopant concentration in the second epitaxial layer 262 grown
5 fluctuates. These fluctuations in the doping may amount to up to $\pm 15\%$ of the basic doping. Even higher deviations are likewise possible. Moreover, the thickness of the epitaxial layer 262 may be subjected to fluctuations over the cross section of the semiconductor configuration 100. These
10 technology-dictated fluctuations may adversely affect the desired behavior of the lateral channel region 22.

In order to eliminate this influence, an n-conducting channel conduction region 225 is arranged in the second epitaxial
15 layer 262, which channel conduction region also extends into the channel region 22 and, in particular, has a higher doping than the basic doping of the second epitaxial layer 262 and the remaining part of the channel region 22. As a result, the channel conduction region 225 has a significantly higher
20 electrical conductivity than the remaining part of the channel region 22. In on-state operation, the current I is essentially carried within the channel conduction region 225. Consequently, the channel conduction region 225 also largely determines the current control behavior of the semiconductor
25 configuration 100.

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

The channel conduction region 225 is formed by means of the
implantation of n-conducting dopant particles into the second
epitaxial region 262. The doping of the channel conduction
region 225 can thus be set very exactly. In particular, in
5 contrast to a layer produced epitaxially, no comparable
fluctuations in doping and thickness result. The substantial
proportion, that is to say in particular at least 80%, of the
total doping of n-conducting charge carriers present within
the channel region 22 is situated in the channel conduction
10 region 225. In the example shown, the implanted dopant
concentration in the channel conduction region 225 is chosen
such that an average dopant concentration of approximately
 $2 \times 10^{16} \text{ cm}^{-3}$ is present in the entire channel region 22. This
corresponds to a customary dopant concentration, which is
15 present in a manner distributed uniformly within the channel
region 22 in the case of a semiconductor configuration (not
shown) without a channel conduction region 225. While in the
case of this embodiment which is not shown, however, the
epitaxy-dictated fluctuations in the dopant concentration
20 significantly influence the behavior of the channel region 22,
the fluctuations of the second epitaxial layer 262, which is
now provided with a basic doping of approximately $7 \times 10^{15} \text{ cm}^{-3}$,
have practically no influence on the current control behavior
of the semiconductor configuration 100. The principal part of
25 the total charge present in the channel region 22 is situated

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

in the channel conduction region 225 produced practically
without doping fluctuations.

A further advantage of the semiconductor configuration 100
5 compared with the embodiment (not shown) without a channel
conduction region 225 is that the channel conduction region
225, in the off-state situation, at least largely or even
completely prevents an otherwise possible field punch-through
into the channel region 22 and an accompanying shift in the
10 pinch-off voltage.

On account of the ion-implanted channel conduction region 225,
the semiconductor configuration 100 can be produced in a
reproducible manner with a very high yield and very precisely
15 defined electrical properties (e.g. pinch-off voltage,
punch-through voltage, channel resistance, saturation current,
reverse voltage). If a semiconductor wafer is used as usual
during fabrication in order to be able to produce many
semiconductor configurations 100 simultaneously, then a very
20 high homogeneity of the dopings in all of the channel
conduction regions 225 is achieved across the complete
semiconductor wafer on account of the ion implantation used.

The depletion zone 24, which concomitantly influences the
25 channel region 22, can be brought about in different ways

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

within the first semiconductor region 2. Embodiments known
from WO 00/16403 A1, for example, for this purpose comprise a
Schottky contact or MOS (Metal Oxide Semiconductor) contact
arranged on the first surface 20.

5

Furthermore, it is also possible, as in the case of a
semiconductor configuration 101 shown in figure 2, to arrange
a second semiconductor region 4 at the first surface 20 within
the first semiconductor region 2. The semiconductor region 4
has the opposite conductivity type to the first conductivity
type of the first semiconductor region 2, that is to say has
the p-conductivity type in the exemplary embodiment
illustrated. It is preferably produced by ion implantation.
The second semiconductor region 4 is in particular heavily
p-doped (p^+). In particular, a volume element of the second
semiconductor region 4 has a total charge quantity of
activated dopants which is at least 5 times, preferably at
least 10 times, higher than in a comparable volume element of
the channel region 22. In this case, the comparison volume
element of the channel region 22 comprises a part with the
basic doping but also a part with the higher doping of the
channel conduction region 225. A p-n junction is present
between the first semiconductor region 2 and the second
semiconductor region 4, the depletion zone of said p-n
junction forming the depletion zone 24 shown in figure 1. For

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

reasons of improved clarity, no depletion zones are depicted
in the semiconductor configuration 101 of figure 2. A control
electrode 40 makes ohmic contact with the second semiconductor
region 4, so that the extent of the depletion zone 24 and thus
the current flow in the channel region 22 and in the channel
conduction region 225 can be influenced by means of an
external control voltage.

The semiconductor configuration 101 is an active arrangement
since the current flow within the semiconductor configuration
101 can be influenced by means of an external measure (control
voltage). However, other embodiments (not shown here) are also
known, for example from WO 00/16403 A1, which lead to a
passive current control and which, in principle, may likewise
be combined with the advantageous channel conduction region
225 for the purpose of carrying current and current control.

Furthermore, the semiconductor configuration 101 of figure 2
is a normally on structure. This means that when there is no
voltage present at the control electrode 40, the channel
region 22 and/or the channel conduction region 225 are open,
that is to say not pinched-off. At a control voltage of zero,
current can thus flow. A normally off embodiment, which is
likewise possible, in principle, and in the case of which the
channel region 22 and the channel conduction region 225 are

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

pinched-off if no control voltage is present at the control
-----electrode 40 is not illustrated. The thickness (= vertical
dimension) of the second epitaxial layer 262 or of the channel
region 22 is then chosen such that the space charge zones 23
5 and 24 which are illustrated in figure 1 and which form on
account of the so-called built-in potentials mutually at least
touch one another and thus completely pinch-off the channel
region 22 and the channel conduction region 225. In order to
enable a current flow, a positive control voltage would then
10 be necessary in the case of an exemplary embodiment which is
comparable to the semiconductor configuration 101 of figure 2
but is a normally off exemplary embodiment. In the case of
this normally off embodiment, too, the channel conduction
region 225 can essentially be used with the same advantages as
15 in the case of the normally on embodiments.

Figure 3 illustrates a typical doping profile for a channel
conduction region 225. In the diagram, a dopant concentration
ND is plotted against a depth T of the channel region 22, said
20 depth also being depicted in figure 2. The basic doping of the
second epitaxial layer 262 can be discerned, as can the
additional doping introduced into the channel conduction
region 225 by ion implantation.

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

The channel conduction region 225 results in an additional
degree of freedom in the design of the semiconductor

configuration 100 or 101. The current-carrying behavior is
principally determined by the doping within the channel

5 conduction region 225, whereas the basic doping of the rest of
the channel region 22 and of the second epitaxial layer 262 is
of secondary importance in this regard. The basic doping can
thus be selected according to other standpoints. In
particular, it is favorable if the basic doping of the second
10 epitaxial layer 262 is equal to the doping of the first
epitaxial layer 261, the latter doping essentially being
determined by the reverse voltage to be carried. No jump in
doping is then produced at the interface 80 between the two
epitaxial layers 261 and 262. Such a jump in doping might
15 otherwise lead, in the off-state situation, to undesirable
field distortions in the boundary region of the two epitaxial
layers 261 and 262, which might result in a limitation of the
maximum reverse field strength that can be utilized or the
maximum reverse voltage that can be achieved.

20

Figure 4 illustrates a particularly favorable semiconductor
configuration 102, in the case of which the high concentration
of n-conducting charge carriers in the channel conduction
region 225 is at least partly compensated for by p-conducting
25 channel compensation regions 226. To be more specific, a

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

highest possible charge carrier concentration is desirable in
order to achieve a best possible current conductivity in the
channel conduction region 225. On the other hand, however, an
excessively high charge carrier concentration leads to an
5 increase in the pinch-off voltage that is to be applied to the
control electrode 40 and is necessary in order to completely
pinch-off the channel region 22. On account of the channel
compensation regions 226 embedded in the channel conduction
region 225, the pinch-off voltage is not increased undesirably
10 even if a very high dopant concentration is provided within
the channel conduction region 225. In an expedient manner, the
total charge of p-conducting charge carriers situated within
all the channel compensation regions 226 is approximately
equal in magnitude to the total charge of all the n-conducting
15 charge carriers of the channel conduction region 225. In order
to achieve this, the dopant concentration is higher in the p-
conducting channel compensation regions 226 than in the n-
conducting channel conduction region 225. The reason for this
is the larger basic area of the channel conduction region 225
20 compared with the basic area of all the channel compensation
regions 226.

These area relationships are clearly apparent from the cross-
sectional illustration of the channel conduction region 225
25 and of the channel compensation regions 226 as shown in figure

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

5. The course of the current I within the channel conduction
region 225 is likewise depicted in figure 5. In addition to
the round geometry illustrated, the cross-sectional area of
the channel compensation regions 226 may also assume other
5 forms, for example a square form or a strip form.

The advantageous effect of the channel region 225 may also
advantageously be employed in the case of other embodiments of
the semiconductor configuration that are possible, in
10 principle, for example in the case of a semiconductor
configuration 103 in accordance with figure 6 or in the case
of a semiconductor configuration 104 in accordance with figure
7. Apart from the channel conduction region 225, the
semiconductor configuration 103 is known from WO 00/16403 A1
15 and the semiconductor configuration 104 is known from DE 198
33 214 C1. Precisely as in the case of the semiconductor
configurations 100, 101 and 102 disclosed in the previous
figures, the semiconductor configurations 103 and 104 are also
a junction field effect transistor in each case, which are
20 realized in particular in the semiconductor material SiC.

In addition to the semiconductor configurations 100 to 104
shown in figures 1, 2, 4, 6 and 7 there are also embodiments
in which a p-conducting substrate 28 is used instead of the
25 n-conducting substrate 27. Such a semiconductor configuration

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

105 is shown by way of example in figure 8. This involves a
vertical JFET with a rear-side bipolar emitter (= BiFET). The
first semiconductor region 2 is then composed only of the two
n-conducting epitaxial layers 261 and 262 and forms a p-n
5 junction with the p-conducting substrate 28. This additional
p-n junction is favorable particularly in the case of use at a
high voltage which, by way of example, is at least of the
order of magnitude of a few kV.

10 It is further favorable that, in on-state operation, holes are
injected via the contact 60 and electrons are injected via the
contact 50 into the semiconductor configuration 105. This
gives rise to a great increase in the charge carrier
concentration. This bipolar modulation of the charge carrier
15 concentration leads to a particularly good current conduction
behavior.

In order to prevent the p-conducting island region 3 from
directly extracting the holes injected from the electrode 60
20 and the concentration of the charge carriers available for
current transport in particular below the channel conduction
region 225 from decreasing on account of this, a heavily
n-conducting shielding region 31 is preferably provided
between the first semiconductor region 2 and the island region
25 3. The shielding region 31 represents an effective barrier

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

against a direct flowing-away of the injected holes into the island region 3. As a result, a favorable high bipolar charge carrier concentration is preserved below the channel conduction region 225.

5

The dopant concentration of the shielding region 31 is typically one to two orders of magnitude above that of the first epitaxial layer 261. It is approximately 10^{17} cm^{-3} in the example shown. The shielding region 31 surrounds the island region 3 in particular on the sides facing the substrate 28 and the vertical channel region 21. However, this complete shielding is not absolutely necessary. The shielding region 31 may also be provided only in regions below the island region 3.

15

The channel conduction region 225 also has a similarly positive shielding effect to the shielding region 31. It prevents the holes from flowing away into the p-conducting second semiconductor region 4. In addition to the improved modulation of the charge carrier concentration, this reduces the leakage current via the control electrode 40.

In alternative embodiments, the conductivity types provided in the respective regions in all of the semiconductor

Application No. 10/549,784
Translation of PCT/DE03/00906
Response to Notification dated 5/8/06

configurations 100 to 105 shown may also assume the
respectively opposite conductivity type.

In every embodiment, the channel conduction region 225 has a
5 favorable effect on the current control behavior and leads, in
particular, to a production process that is largely
independent of technology-dictated fluctuations. It is thus
possible in each case to obtain a very high yield during
production. It is favorable, moreover, that the respective
10 channel region 22 can be formed with a smaller height on
account of the more defined setting of the channel properties.
The channel length can then also be reduced without any losses
in the reverse voltage strength. The ratio of channel length
to channel height is also critical for the reverse voltage
15 strength. This ratio is greater than 1, preferably 5 and
greater. In the case of the respective semiconductor
configurations 100 to 105, the channel length concomitantly
determines the space requirement and also the resistance in
on-state operation ($= R_{on}$). Both characteristic quantities thus
20 decrease with a reduction of channel height and channel length
possible by virtue of the channel conduction region 225. A
smaller space requirement enables a higher cell density of
semiconductor configurations 100 to 105 that can be
accommodated on a semiconductor wafer. The yield also
25 increases as a result of this.

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record.**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☐ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☒ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☒ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER:** _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.